# BARIX


# **Barionet 400 InformaCast**

I/O device to implement into Singlewire's InformaCast notification system.



Barix Barionet 400 InformaCast is a PoE powered I/O device server which is certified for Singlewire's mass notification system InformaCast adopting the M2M capability. The device features four digital inputs and four relays. Extension of the functionality via the USB port

and via a programming interface is possible as an option. The Barionet 400 devices provides a robust bridge between the InformaCast notification system and physical interfaces such as distress buttons, fire alarm panels, motion sensors, light switches, door activators and more.



### Applications

Integration into Singlewire's InformaCast for:

- Control of emergency alerts with time-sensitive information
- Automated actions when an event is triggered, such as closing of doors, power of lights, screens, horns, transport options or shutting down of building infrastructure
- Access control
- Machine control

### Features

- Configurable on Singlewire InformaCast Server
- One 10/100 Ethernet port
- 4 Relay Outputs
- 4 Digital Inputs
- USB Host Interface
- Embedded Linux / Lede / OpenWRT
- IPv4 / IPv6 stack
- Barionet DIN-Rail Case
- Supply Voltage 9-30 VDC
- IEEE 802.3af PoE

## **Technical Specifications**

#### **Operation System**

• Linux / Lede / OpenWRT

#### **Network / WiFi Interfaces**

- 1 x Ethernet (RJ45) Interface
- IPv4, IPv6 capable
- 10/100 fdx/hdx, auto negotiation
- TCP/IP, RTP, UDP, ICMP, DHCP, CGI, HTTP(S), SNMP (used to "talk" to InformaCast)

#### I/O Interface

- 4 x Relay Outputs (30VDC, 0.5A)
- 4 x Digital Inputs (dry contacts)

#### **USB** Interface

• 1 x USB Host (Type A) Interface

#### **CPUs / Memory**

- MediaTek MT7620N, Qino Lite Module
- 64MB SDRAM
- 8MB Flash

#### **OEM Options**

• RTC Real Time Clock

#### **User Interface**

- Web interface for control / configuration
- 10 x Multicolor LED Status indicators
- Reset & Factory Defaults Button

#### **Power Requirements**

- Single 9-30V DC supply voltage, 2.5 Watt (without attached USB devices) or
- IEEE 802.3af PoE

#### Measurement

• 4.05" x 3.35" x 1.22" / 103mm x 85mm x 31mm

#### Weight

• 160g

#### Warranty

• Two years

## Environmental

#### **Operating Environment**

0 to +50°C / 32 to 122°F 0 - 70% relative humidity, non-condensing

#### **Storage Conditions**

-20 to +70°C / -4 to 158°F 0 - 70% relative humidity, non-condensing

## Certifications

CE, RoHS, FCC

## **Ordering Information**

2018.9257P BARIONET 400 (incl. InformaCast)



For commercial related questions (distributors contacts, price list, business opportunities) please contact: <a href="mailto:sales@barix.com">sales@barix.com</a>



For technical inquiries (problem reports, request for documentation, etc.) please contact: <a href="mailto:support@barix.com">support@barix.com</a>

**Barix AG** 

Limmatstrasse 21, 8005 Zürich, Switzerland Phone: +41 434 33 22 11 www.barix.com



© Barix AG 2021, all rights reserved. All information is subject to change without notice. All mentioned trademarks belong to their respective owners and are used for reference only. Product Sheet V1.4